XRP Proxtend HP ONLINE UPS

Critical Power Protection, Zero Downtime!

The XRP ProXtend HP UPS presents optimized robust power protection & performance, highest availability & versatility for harshest industrial environments, healtcare and datacenter applications whilst reducing TCO & minimising the time for ROI.

Key Features

- * IGBT rectifier, IGBT inverter, PWM technology
- * Built-in output isolation transformer
- * DSP controlled, highly-efficient





















& Proces Control

Data Centers Environment

& Facilities

Telecom Emergency Applications Applications

Transportation

Product Snapshot

Delivers An Outstanding Power Performance & Increased Power Quality

- True VFI | online double conversion design guarantees the complete isolation of critical load from any mains disturbances.
- High frequency, IGBT rectifier & inverter design via PWM technique presents active power factor correction at input which lowers THDi at input & maximizes the input power factor as > 0,99. This leads minimized generator: UPS sizing, less investment and costs due to very low harmonics. The system reduces the effect on utility and the loads connected to the same network with the ups itself.
- IGBT design at the inverter stage also brings high output power as 0,9 or 1 Unity PF [kVA=kW] while reducing the THDv as low as 1%. • Twin DSP microprocessor control offers maximized reliability, total
- protection of UPS & critical load aganist failures & damages, unbeatable parallel redundant operation in business-critical environments & applications.
- Compact design which brings ease of transport, installation and maximizes power density in minimum footprint as low as 1,45 m2 for a 250 kVA UPS.
- Its built-in output isolation transformer brings greater adaptability, versatility in system configurations, higher immunity to harmonics, sudden inrush currents & energy backfeed generated by the load & environments with with high RFI [loads compliant like CNC, CT]

Controlling Both CAPEX and OPEX

- Delivers industry leading AC~AC online double-conversion efficiency without sacrificing reliability. Thanks to its highly efficient design, savings can reach up to 35% in dissipated energy in one year compared to traditional legacy UPS systems resulting in a faster payback period of 4 years as ROI.
- HVAC systems and cooling infrastructure initial investment is kept at minimum while cooling costs such as power, maintenance of HVAC units are at minimum. Keeping power & cooling infrastructure cost at minimum [CAPEX] along with operating costs at minimum [OPEX], ProXtend HP gives the power of control.
- Scalability Pay as You Grow! Capacity can flex to meet power infrastructure growth by adding an additional ups in the field, ease of expansion from medium-sized installations to hyperscale infrastructures.

The UPS XRP ProXtend HP: Power Protection & More

The XRP ProXtend HP is a next-generation VFI | online double conversion high frequency three phase UPS which offers high electrical & mechanical robustness, high reliability for various industries & applications. The UPS uses the latest IGBT-PWM technology & DSP control to provide maximum power protection performance, increased power quality & clean, continuous power for any type of application.

The UPS **ProXtend HP** offers one of the lowest TCO & fastest ROI in the industry with its high efficieny values and power density. Its robust design, proven reliability and maximised availability which dramatically decrease operational downtimes and costs during its lifetime and true scalability makes it indispensible to various industries worldwide.

Advanced battery care design, zero impact on utility, generators & loads connected to the UPS itself also makes it superior by the proven data aganist traditional legacy ups system along with many rivals existing in the market.

The UPS ProXtend HP is engineered to meet the needs of demanding environments & businesses worldwide.

Advanced Battery Care

The UPS **ProXtend HP** provides extended service life for batteries via its three stage charging mode. Thanks to its innovative software helps the user to monitor battery health & remaining back up period, extended scalable battery runtimes is not a matter with the UPS ProXtend HP.

Reliability, Availability and Serviceability (RAS)

Maximized availability and reliability by the power engineering at its top level, ProXtend HP offers very robust & reliable power protection, this also leads minimized downtime and highest level of availability. Very high level of MTBF [Mean Time Between Failures] and very low MTTR [Mean Time to Repair] ensures the critical load not to fail for its duty. Serviceability is a measure of the system to be recovered after a disaster. A min. of 15 mins. of enough for a technician to diagnose and recover the system to reduce the downtime for business.



Technical Specifications

160 200 250 300 400

500 600

UPS Rating

Rated Power [kVA]

Rated Power [kVA]	160	200	250	300	400	500	600	
Active Power [kW] [for Model S]		160	200	240	320	400	480	PF = 0
Active Power [kW] [for Model E]	144	180	225	270	360	450	540	PF = 0
General Characteristics								
MTBF/ MTTR	Over 2	50000 F	Hours/ Be	elow Tha	n 15 Mii	nutes		
			uble Co					
JPS Type & Technology			on of Outp cy Opera					
			oprocess					
52040-3	COMP	ATIBLE						
Power Factor	0.9 (as	Standar	rd, PF : 0	,8 Versic	n is Ava	ilable)		
nput Voltage Range	-45%	~ +27%	[at 64%	Rated L	oad]			
Output Isolation Transformer	Built-ir	n, Standa	ard, For I	Heavy D	uty Appl	ications		
rue Redundancy	N+X, N	N+1 Redu	undant C	onfigura	ations			
Parallel Configuration [N+1]	Up To	8 Units						
araner corrigaration [ivv-i]			miting, P	hase Re	versal P	ower Mo	idule Ov	er Tem-
Standard Protection	peratu	re, Ove	r Currer	nt, High "	Tempera	ature Ale	rt, Smart	Short
Features			erative L					Current
			erature e Protec					
Operating Conditions			m Above				6 RH,	
<u> </u>			mance a					
Cooling/ Isolation				Redunda	ant Fans	, Smart F	an Spee	d Contro
		E with 0).9 PF e not ava	nilabla G	raphical	l Elow Di	aaram ic	Head
			ass, Batte					USCU
Display & Parameters	Equipp	ed with						
Display & Parameters	Equipped with 3,5" Graphical Touchscreen LCD Display:							
	Input, Bypass, Output Voltages [V] & Frequency [Hz], Input							
	Input,	Bypass, (
	Input, &	<i>Bypáss, (</i> out Curr	Output N ents [A], utput Ac	Load Ci	urrents [A], Outp	ut Appe	
	Input, & Outp & Outp Power Percer	<i>Bypass, (</i> out Curro [VA], Oo otages [%	ents [A], utput Ac 6] for Ea	Load Co tive Pow ch Phase	urrents [er [W], (e, Batter)	A], Outp Output P y Voltage	ut Appe F, Load es for + a	arent & - String
	Input, & Outp Power Percer Battery	Bypass, (out Curro [VA], Oo Itages [% Current	ents [A], utput Ac 6] for Ea t, Battery	Load Ci tive Pow ch Phase Tempe	urrents [er [W], (e, Batten rature [^c	A], Outp Output P y Voltage C], Rem	ut Appe F, Load es for + a aining Ba	arent & - String attery Ba
	Input, & Outp Power Percer Battery Up Per	Bypass, (out Curro [VA], Ou stages [% or Current riod [mir	ents [A], utput Ac 6] for Ea	Load Ci tive Pow ch Phase Tempe Bus Volta	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
	Input, a & Outp Power Percer Battery Up Per Tempe 512 pc	Bypass, (out Curro [VA], Ou atages [% or Current riod [miro erature [9 s Events	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo	Load Ci tive Pow ch Phase Tempe Bus Volta	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Maintenance Bypass	Input, & Outp Power Percer Battery Up Per Tempe	Bypass, (out Curro [VA], Ou atages [% or Current riod [miro erature [9 s Events	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo	Load Ci tive Pow ch Phase Tempe Bus Volta	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
	Input, a & Outp Power Percer Battery Up Per Tempe 512 pc	Bypass, (pout Curre [VA], Outages [% (Current Friod [mirerature [9] (SEVENTS)	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo	Load Ci tive Pow ch Phase Tempe Bus Volta	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour	Input, & Out ₁ & Out ₁ Power Percer Battery Up Per Tempe 512 pc STANE	Bypass, () out Curri [VA], Ou itages [% r Curren iod [mir erature [4] s Events DARD	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry	Input, & Out ₁ & Out ₁ Power Percer Battery Up Per Tempe 512 pc STANE	Bypass, () out Curri [VA], Ou itages [% r Curren iod [mir erature [4] s Events DARD	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry	Input, & Outp Power Percer Battery Up Per Tempe 512 pc STANE BLACK REAR/	Bypass, (put Curri [VA], Outages [% of Currential Minimum of Minim	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode	Input, & Outp Power Percer Battery Up Per Tempe 512 pc STANE BLACK REAR/	Bypass, (put Curri [VA], Outages [% or Currention [Minimum] initial [%] s Events DARD FRONT	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode	Input, & Outperson Percer Battery Up Per Temper 512 pc STANE BLACK REAR/	Bypass, () out Currice [VA], Out Currice trages [% out Current riod [mire rature [4] s Events DARD FRONT	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode	Input, & Outp Power Percer Battery Up Per Tempe 512 pc STANE BLACK REAR/	Bypass, () out Currice [VA], Out Currice trages [% out Current riod [mire rature [4] s Events DARD FRONT	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode	Input, & Outperson Percer Battery Up Per Temper 512 pc STANE BLACK REAR/	Bypass, () out Currice [VA], Out Currice trages [% out Current riod [mire rature [4] s Events DARD FRONT	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Pow ch Phase Tempe Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode	Input, & Out, Power Percer Battery Up Per STANE BLACK REAR/ Up To > 98% < 97%	Bypass, () out Curri, (VA), Outages [N) or Currentiages [N) or Cur	ents [A], utput Ac 6) for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Power to Phase y Tempee Bus Volta ller Heat	urrents [er [W], (e, Batten rature [^c ages for	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode nput Characteristics	Input, & Outp. Power Percer Battery Up Per Tempse 512 pc STANE BLACK REAR/ Up To > 98% < 97%	Bypass, (out Curricular) (pva), Out Curricular) (pva), Out Curren (pva), Out (mirren (pva	ents [A], utput Ac 6] for Ea t, Battery ns.], DC E °C], Coo Log	Load Ci tive Powc ch Phase r Tempe Bus Volta ller Heat	urrents [which was a control of the	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode nput Characteristics	Input, . & Outy Power Percer Battery Up Per STANE BLACK REAR/ Up To 98% < 97% 380/4 4 -15% -45% -	Bypass, () Bypass, () Bypass, () Bypass, () Bypass, () Bylass, () Bylass, () Current Current Current Se Events ARD FRONT FRONT 00/415 +27%	ents [A], utput Ac 6) for Eac 6) for Eac t, Battery ss.], DC E °C], Coo Log	Load Cu tive Pow h Phase Tempe Sus Volta Heat HN+PE Rated L Rated L Rated L Rated L	urrents [c]	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode nput Characteristics Rated Voltage & Range	Input, . & Outy Power Percer Battery Up Per STANE BLACK REAR/ Up To > 98% < 97%	Bypass, () Bypass, () Bypass, () Bypass, () Bypass, () Bylan, () B	ents [A], utput AC [A] (b) for Ea t, Battery s.s.], DC E CC], Coo Log VAC 3P- VAC 3P- VAC 3P- (at 100%) [at 104%]	Load Ci titive Pows to he Phase ty Tempee Sus Voltati ler Heat WM	urrents [c], but a control of the co	A], Outp Output P y Voltage (C], Rem + & - St	ut Appe F, Load es for + a aining Ba rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range	Input, & Outy Power Percer Battery Up Per Tempe 512 pc STANLE BLACK REAR/ Up To > 98% < 97%	Bypass, () Bypass, () Bypass, () Bypass, () Bylan, () By	ents [A], utput AC [A] (b) for Ea t, Battery s.s.], DC E CC], Coo Log WAC 3P- [At 100% [at 100% [at 42% [at 42% [c] Conline [at 42% [c] Colline [at 42% [c] Colline [c] Co	Load Ci titive Pows to he Phase ty Tempee Bus Voltalier Heat WM	urrents [c] (in the property of the property o	AJ, Output P VOltage V VOltage + & - St nperature	ut Appe F, Load ses for + i aining B; rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range	Input, . & Outy Power Percer Battery Up Per STANLE BLACK REAR/ Up To > 98% < 97% 380/4 4 -15%45%64% - 50/60 > 0,99	Bypass, () Bypass, () Bypass, () Bypass, () Bylan, () By	ents [A], utput AC [A] (b) for Ea t, Battery s.s.], DC E CC], Coo Log VAC 3P- VAC 3P- VAC 3P- (at 100%) [at 104%]	Load Ci titive Pows to he Phase ty Tempee Bus Voltalier Heat WM	urrents [c] (in the property of the property o	AJ, Output P VOltage V VOltage + & - St nperature	ut Appe F, Load ses for +, and an ining B; rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range	Input, & Outy Power Percer Battery Up Per Tempe 512 pc STANLE BLACK REAR/ Up To > 98% < 97%	Bypass, () Bypass, () Bypass, () Bypass, () Bylan, () By	ents [A], utput AC [A] (b) for Ea t, Battery s.s.], DC E CC], Coo Log WAC 3P- [At 100% [at 100% [at 42% [at 42% [c] Conline [at 42% [c] Colline [at 42% [c] Colline [c] Co	Load Ci titive Pows to he Phase ty Tempee Bus Voltalier Heat WM	urrents [c] (in the property of the property o	AJ, Output P VOltage V VOltage + & - St nperature	ut Appe F, Load ses for +, and an ining B; rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode mput Characteristics Rated Voltage & Range Rated Frequency & Range Power Factor Current Distortion [THDi]	Input, . & Outy Power Percer Battery Up Per STANLE BLACK REAR/ Up To > 98% < 97% 380/4 4 -15%45%64% - 50/60 > 0,99	Bypass, () Bypass, () Bypass, () Bypass, () Bylan, () By	ents [A], utput AC [A] (b) for Ea t, Battery s.s.], DC E CC], Coo Log WAC 3P- [At 100% [at 100% [at 42% [at 42% [c] Conline [at 42% [c] Colline [at 42% [c] Colline [c] Co	Load Ci titive Pows to he Phase ty Tempee Bus Voltalier Heat WM	urrents [c] (in the property of the property o	AJ, Output P VOltage V VOltage + & - St nperature	ut Appe F, Load ses for +, and an ining B; rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range Power Factor Current Distortion [THDi]	Input, . & Outy . Power Percer Battery Up Per STANLE BLACK REAR/ Up To > 98% < 97% 380/4 - 15% - 64% - 50/60 > 0.99 < 3%	Bypass, () Bypass, () Bypass, () Graphysis () Bysass, () Graphysis () Bysass, () By	ents [A], utput AC [A] (b) for Ea	Load Cu titive Pow how ho Phase y Tempe Sus Volta ler Heat W W HN+PE Rated L Rat	urrents [er [W], e., Battere [v] and a series [v] and a s	AJ, Output A	ut Appe F, Load ses for +, Load rings, Int	arent & - String attery Ba
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range Power Factor Current Distortion [THDi] Battery Rated Voltage [DC]	Input, . & Outy . Power Percer Battery Up Per STANE BLACK REAR/ Up To > 98% < 97% 380/ 4 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	Bypass, () Bypass, () Bypass, () Graphysis () Bysass, () Graphysis () Bysass, () By	ents [A], utput AC [A] (b) for Ea	Load Cu titive Pow how ho Phase y Tempe Sus Volta ler Heat W W HN+PE Rated L Rat	urrents [er [W], e., Battere [v] and a state [AJ, Output A	ut Appe F, Load ses for +, Load rings, Int	arent & - String attery Bar ernal
Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range Power Factor Current Distortion [THDi] Battery Rated Voltage [DC] DC Input Voltage Range	Input, . & Outy Per Percer Battery Up Per Tempe 512 pc STANE BLACK REAR/ Up To > 98% < 97% 380/4 -15%45%45%45%30 - 60% - 0.99 < 3% - 720 \ 100 -	## Bypass, () Bypass, () Bypass, () WAJ, Oil WAJ WAJ WAJ WAJ WAJ WAJ WAJ WA	ents [A], utput AC [A], log for Ea [A]	Load Cit titive Pow Arther Phase Temperature Temperatu	urrents [er [W], e., Batterer [W], oad] ooad] ooad] ooad] obad] orrection	AJ, Output P Voltage Voltage PCJ, Rem + & - St nperature	ut Appe F, Load ses for + i aining B; rings, Int e [°C],	arent & - String attery Bar ernal
Maintenance Bypass Material [Casing]/ Colour Cable Entry Efficiency AC~AC Mode Eco-Mode DC~AC/ Battery Mode Input Characteristics Rated Voltage & Range Rated Frequency & Range Power Factor Current Distortion [THDi] Battery Rated Voltage [DC] DC Input Voltage Range Intelligent Battery Managemen Charging Capacity	Input, & Outy & Outy Power Percer Battery Up Per Temps 512 pc STANLE BLACK REAR/ Up To > 98% < 97% 380/4 4 -15%45%64% 50/60 > 0,99 < 3% 720 0 600- tt Temps Deep	Bypass	ents [A], utput AC [A], utput AC [A]	Load Ci titive Pows to h Phase y Tempe Bus Voltati ler Heat MM	urrents [c] (F) (A) (A) (A) (A) (A) (A) (A) (A) (A) (A	AJ, Output P Voltage Voltage A - St nperature a Circuitr cee Seale	ut Appe F, Load ses for + i aining B; rings, Int e [°C],	arent & - String attery Bar ernal

tsinepower

TSINE ELEKTRONİK SANAYİ VE TİCARET LTD. ŞTİ.

Beyit St., No: 55/4, Yukarı Dudullu, Umraniye P.O. BOX: 34775 İSTANBUL / TURKEY





Output Characteristics

Power Factor	±0,01% (Free Running Mode, Selectable) 0.9 (as Standard, PF : 0,8 Version is Available)
Voltage Distortion [THDv]	2% (at 100% Linear Load)
Crest Factor	3:1
Unbalanced Load & Acceptable Load PF	Compatible with Operation on 100% Unbalanced Load 0,9 Leading to 0,9 Lagging without Any Degradation
Overload Operation	10 mins @ 100% ~ 125% Rated Load 60 seconds @ 150% Rated Load Switches to Bypass Line over 150% Rated Load

50/60 Hz, ±6% [Adjustable]

Rated Frequency & Range Communication & Supervision

	Model E with 0.9 PF
	Standard (Available As Hardware & Software): RS232 Serial
	Comm. Port, RS485 (MODBUS) Serial Comm. Port, SNMP Slot,
	EPO-Emergency Power OFF Button, Generator Interface,
	Programmable 4 pieces Dry Contacts from Front Panel for Any
Remote Monitoring	of The Following Signals : General Alarm, Mains Failure, Battery
&Management	Failure, Output Failure, Load on Bypass, Output Overload, High
awanagement	Temperature

Optional (Standard in Software, Optional as Hardware): SNMP - Network Management Kit [External or Internal], Remote Monitoring & Management Panel, TCP/IP converter, GSM/GPRS Modem, Communication Ports Multiplier.

Environment

Operating Temperature Range Prespecified Operating T. Storage Temperature	0°C - 40°C/20°C - 25°C/-30°C ~ 60°C				
Altitute/ Relative Humidity	< 1000m above sea	level/ < 95% (non-condensing)			
Noise	< 62 dBA	< 67 dBA			

Certifications

Certifications	
Safety	EN 62040-1
Electromagnetic Compability [EMC]	EN 62040-2
Performance [VFI-SS-111]	EN 62040-3
Safety	EN 60950-1 Information Technology Equipment
Quality Management	CE, ISO 9001:2015, ISO 14001:2015

Optional Features & Accessories

Custom Input Voltage Range	Optional				
IP Classified Enclosure	Available from IP21 ~ IP 66				
Others	Paralelling Kit, Network Management Kit, External Bypass, Remote Monitoring & Management Panel, UPS Looking Battery Enclosuresetc				

Physical	UPS Rating [kVA]	160	200	250	300	400
Dimensions [mm]		980*870*1950	1	1340*108	0*1950	
Weight [kg]		570	760	785	875	1000
Protection Degree		IP20 (Standard)				

UPS Rating [kVA]			Model Names & Codes
160	200	250	XRP09160HPPX XRP09200HPPX XRP09250HPPX
300	400	500	XRP09300HPPX XRP09400HPPX XRP09500HPPI
600	800		XRP09600HPPI XRP09800HPPI